

VISION

TECHCONNECT OWNERS MANUAL
TECHCONNECT GUIDE DE L'UTILISATEUR
TECHCONNECT MANUAL DE USUARIO
TECHCONNECT GEBRUIKERSHANDLEIDING
BEDIENUNGSANLEITUNG TECHCONNECT
TECHCONNECT MANUALE DEL PROPRIETARIO

TECHCONNECT OWNERS MANUAL

Congratulations on your choice of the Vision TECHCONNECT. In order to obtain the best performance, please be sure to read this owner's manual and use your product only in accordance with instructions. An electronic version of this manual and further information can be found on www.visionaudiovisual.com

CONFORMITY

The product described in this owners manual is in compliance with RoHS (EU directive 2002/95/EC), and WEEE (EU directive 2002/96/EC) standards. Certificates including SGS reports are available on request. This product should be returned to the place of purchase at the end of its useful life for recycling.



This document has been downloaded from:



Touch AV Ltd.

Suppliers of Vision products in the UK




www.touchaudiovisual.co.uk

WIRING DIAGRAM

VGA & MiniJack Snap-in Module:

TECHCONNECT PHOENIX LABEL	SIGNAL TYPE	CABLE COLOUR	CONNECTOR PIN
RI	Audio Right	Red	
g	Audio Ground	Shield	
LE	Audio Left	White	
R	Red	Red	Pin 1
Rs	Red Ground	Red Shield	Pin 6
G	Green	Green	Pin 2
Gs	Green Ground	Green Shield	Pin 7
B	Blue	Blue	Pin 3
Bs	Blue Ground	Blue Shield	Pin 8
H	Horizontal Sync	Brown	Pin 13
Syg	Sync Ground	Black	Pin 10+5
V	Vertical Sync	Yellow	Pin 14
SCL	DDC2B Bidirectional Data Line	Gray	Pin 15
SDA	DDC2B Data Clock	White	Pin 12
SH	Chassis Ground	Shield	Outer Shield



Note: The outer shield of the VGA cable should remain un-terminated
 There is no colour standard for the Horizontal and Vertical Sync cables, so if you use cables not included with the Techconnect, you will need to use a continuity tester to determine which colour on your cable matches which pin on your cable.

S-Video Module:

TECHCONNECT PHOENIX LABEL	SIGNAL TYPE	CABLE COLOUR	CONNECTOR PIN
Yg	(Y) Luminance Ground	Black	Pin 1
Y Syn	(Y) Luminance+sync	Red	Pin 3
g	Ground		
C	Chrominance	Orange	Pin 4
Cg	Chrominance Ground	Brown	Pin 2



3-Phono Module:

TECHCONNECT PHOENIX LABEL	SIGNAL TYPE	CABLE COLOUR
LE	Left Audio	White
LEg	Left Audio Ground	White Shield
RI	Right Audio	Red
RIg	Right Audio Ground	Red Shield
V	Composite Video	Yellow
Vg	Composite Video Ground	Yellow Shield

TROUBLE SHOOTING

If you experience a problem, you should narrow down if the problem is with a faulty cable, or a faulty snap-in module. For example, if you cannot get the VGA output of your computer to work:

1. Test a short 2m VGA cable between the projector and computer to make sure it is working
2. Cut one end off the same cable, strip back wires, and attach to the techconnect module.

If the image is now displayed, the problem is with your long cable and you should replace it. If the problem persists, you have either wired the wrong cables to the wrong terminals, or the module is faulty.

WARRANTY

This product comes with a 2-year return to base warranty, effective from the date of purchase. This warranty applies only to the original purchaser and is not transferable. For the avoidance of doubt, this will be taken from the information held by the appointed national distributor at the point of sale. The liability of the manufacturer and its appointed service company is limited to the cost of repair and or replacement of the faulty unit under warranty, except for death or injury (EU85/374/EEC). This warranty protects you against the following:

- Failure of any snap-in components
- Failure of cables if reported within 24 hours of purchase.
- Corrosion if reported within 24 hours of purchase.

If you find you do have a problem with this product, you should contact the AV reseller you purchased this product from. The original purchaser is responsible for shipment of the product to the manufacturer's appointed service centre for repair.

We will endeavour to return repaired units within 5 working days, however this may not always be possible in which case it will be returned as soon as practically possible. In line with our WEEE commitments, the manufacturer endeavours to replace the faulty parts of the product rather than replacing the whole unit. This warranty does not protect this product against faults caused by abuse, misuse, incorrect installation, unstable or faulty power input, which might be caused by ignoring the guidelines set out in this manual.

If failure is not covered by this warranty, the owner will be given the option to pay for labour and parts to repair the unit at the service company's standard rate.