



# 100w Active Soundbar Plus

SB-1900P EU SAP: 4801694 US SAP: 13445515

[visionaudiovisual.com/sb-1900p](http://visionaudiovisual.com/sb-1900p)

Built-in 2 x 50 watt (RMS) amplifier

HDMI 2 in 1 out

1 x Minijack input

Bluetooth input (re-nameable and pin can be set)

Remote control included

RS-232

ARC HDMI Input (allows display to control volume)

**Need to punch a hole in the back wall? The SB-1900P soundbar outputs truly impressive sound! The chassis has a matt black finish that enhances any audio-visual installation in meeting rooms, boardrooms, and conference rooms.**



### **Rename Bluetooth**

Set any Bluetooth name and Pin. Use PC software to load an image file onto a USB stick. Insert into the soundbar and boot up. The advanced BT chipset allows multiple devices to pair at once.

### **Multiple HDMI**

Two HDMI inputs and an HDMI output make connecting to other devices easy.

### **ARC HDMI**

If a display is connected to the ARC input on the soundbar, the display remote control will control the soundbar volume.

### **Analogue Input**

A stereo line-level Minijack input handles normal analogue sources.

### **RS-232 Control**

For professional integration it features RS-232 control via the USB port.

### **Auto Standby**

Choose to use the standard auto standby setting to conserve power, or hold down VOL+ to disable auto-standby.

### **Hanging Brackets**

A set of brackets are included which hang the soundbar under the flat panel. The speaker also comes with rubber feet if you need to place on a shelf, and wall-hanging lugs.

### **Power Cycling**

If mains power is turned off and on, the SB-1900P will automatically come back on resuming the previous settings.

### **Remote Control**

A remote control is included.

## MANUAL

Hanging bracket quick manual

**EN PDF 110.37 KB**

[files.visionaudiovisual.com/products/SB-1900P/manuals/SB-1900P\\_hanging\\_bracket\\_quick\\_manual.pdf](files.visionaudiovisual.com/products/SB-1900P/manuals/SB-1900P_hanging_bracket_quick_manual.pdf)

Manual

**EN PDF 2.27 MB**

[files.visionaudiovisual.com/products/SB-1900P/manuals/SB-1900P\\_manual\\_en.pdf](files.visionaudiovisual.com/products/SB-1900P/manuals/SB-1900P_manual_en.pdf)

Vision soundbar range overview

**EN PDF 574.00 KB**

[files.visionaudiovisual.com/products/SB-1900P/product/Vision\\_soundbar\\_range\\_overview.pdf](files.visionaudiovisual.com/products/SB-1900P/product/Vision_soundbar_range_overview.pdf)

## IMAGE

Product Images

**ZIP 19.73 MB**

<files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P.zip>

## SPECIFICATIONS

### PRODUCT DIMENSIONS

800 x 90 x 62 mm / 31.5" x 3.5" x 2.4" (width x depth x height)

### PACKAGED DIMENSIONS

1055 x 155 x 105 mm / 41.5" x 6.1" x 4.1"

### PRODUCT WEIGHT

2.1 kg / 4.6 lbs

### PACKAGED WEIGHT

3.6 kg / 7.9 lbs

### CONSTRUCTION MATERIAL

ABS Plastic

### COLOUR

Black

### AMPLIFIER OUTPUT

2 x 50w watts (RMS)

### DRIVERS

4

### DRIVER IMPEDANCE

4 Ohms

### INPUT 1

Aux in (3.5mm) Input Sensitivity: 700mV

### INPUT 2

HDMI(2 in 1 out)

### TOTAL HARMONIC DISTORTION

1% (1kHz, 1W)

### USB-A

for renaming Bluetooth and RS-232 control

### SPEAKER IMPEDANCE

8 ohms

### SENSITIVITY

91 dB (1w/1m)

### FREQUENCY RESPONSE

70Hz-20kHz

### POWER CONSUMPTION

30w (<0.5W standby)

### BLUETOOTH

V4.2

### MAXIMUM POWER TRANSMITTED

<5 dBm

### FREQUENCY BANDS

2402 - 2480 MHz

### POWER INPUT

DC 20V/3A

### REMOTE CONTROL

Distance: 6 m (20ft) Angle: 30° Battery Type: CR 2025

### ACCESSORIES INCLUDED

1 x Remote Control 2 x L shaped universal mounting strips – to hang soundbar beneath flat panel 1 x

USB-A to 9-pin serial adaptor cable, Black 4 x 1.5 m (4.9ft) Figure-8 power cable (right-angle plug: UK/EU/US, normal plug: AU), Black

### POWER SUPPLY

External 100-240v 50/60Hz AC Power Supply – 21 volt / 3 amp. DC tail length: 1.2 m (3.9ft).

Transformer dimensions: 128.9 x 51.3 x 34.8 mm (5.07" x 2.02" x 1.37"), Pin dimensions: Length: 10mm, diameter 6.5mm

### WARRANTY

Lifetime return-to-base

### COMPLIANCE

RoHS, WEEE, CE/EMC, FCC, IEC, RCM-POC, RCM-SDOC, REACH

### ORDER PART CODE

SB-1900P [EU SAP: 4801694 / US SAP: 13445515]

### SPARE POWER SUPPLY

TC2 P21V3A [EU SAP: 4873762 / US SAP: 13445527]

### SPARE REMOTE

SB-1900P RC [EU SAP: 4873590/ US SAP: 13445517]

VISION